


IM5141



Inductive analog sensor with IO-Link

IMC4026A1PKG/IO/US



| Product characteristics | |
|-----------------------------|--|
| Electrical design | PNP/NPN; (configurable) |
| Output function | normally open / closed; (configurable) |
| Communication interface | IO-Link |
| Housing | rectangular |
| Dimensions [mm] | 40 x 40 x 54 |
| Electrical data | |
| Operating voltage [V] | 15...30 DC |
| Current consumption [mA] | < 33 |
| Protection class | II |
| Reverse polarity protection | yes |

IM5141



Inductive analog sensor with IO-Link

IMC4026A1PKG/IO/US

| Outputs | |
|--|--|
| Electrical design | PNP/NPN; (configurable) |
| Output function | normally open / closed; (configurable) |
| Max. voltage drop switching output DC [V] | 2.5 |
| Permanent current rating of switching output DC [mA] | 100 |
| Switching frequency DC [Hz] | 100 |
| Analog current output [mA] | 4...20; (linear; gradient: 0,64 mA/mm; for frontal approach and for target made of mild steel: 90 x 90 x 1 mm) |
| Max. load [Ω] | 500; ($U_b \leq 18$ V;; Max. load ≤ 400 Ω) |
| Short-circuit protection | yes |
| Overload protection | yes |
| Monitoring range | |
| Measuring range [mm] | 1...26 |
| Switch point IO-Link [mm] | 3.44...24.2 |
| Accuracy / deviations | |
| Correction factor | steel: 1 / stainless steel: 0.7 / brass: 0.4 / aluminum: 0.4 / copper: 0.3 |
| Hysteresis [% of Sr] | 3...15 |
| Note on hysteresis | configurable |
| Linearity error of analog output [%] | ± 2 ; (of the final value of the measuring range) |
| Repeatability analog output [%] | ± 2 ; (of the final value of the measuring range) |
| Temperature coefficient [%/K vom MEW] | $\pm 0,15$ |
| Temperature drift | ± 5 %; (of the final value of the measuring range) |
| Reaction times | |
| Response time [ms] | < 20 |

IM5141



Inductive analog sensor with IO-Link

IMC4026A1PKG/IO/US

| Interfaces | | |
|---------------------------------|---|--------------------------|
| Communication interface | IO-Link | |
| Transmission type | COM2 (38,4 kBaud) | |
| IO-Link revision | 1.1 | |
| SDCI standard | IEC 61131-9 | |
| Profiles | Smart Sensor: Identification and diagnosis; Multi-channel, two setpoint switching sensor, type 0 Generic Profiled Sensor; Teach Channel | |
| SIO mode | yes | |
| Required master port class | A | |
| Min. process cycle time [ms] | 3.2 | |
| IO-Link process data (cyclical) | Function | bit length |
| | process value | 16 |
| | device status | 4 |
| | binary switching information | 2 |
| IO-Link functions (acyclical) | switching cycles counter; switch-on cycle counter; operating hours counter; internal temperature; application specific tag | |
| Supported DeviceIDs | Type of operation | DeviceID |
| | default | 1205 |
| Note | For further information please see the IODD PDF file at "Downloads" | |
| Operating conditions | | |
| Ambient temperature [°C] | -25...80 | |
| Protection | IP 67 | |
| Tests / approvals | | |
| EMC | EN 61000-4-2 ESD | 4 kV CD / 8 kV AD |
| | EN 61000-4-3 HF radiated | 10 V/m |
| | EN 61000-4-4 Burst | 2 kV |
| | EN 61000-4-6 HF conducted | 10 V |
| | EN 55011 | class B |
| MTTF [years] | 232 | |
| Embedded software included | yes | |
| UL approval | Ta | -25...70 °C |
| | Enclosure type | Type 1 |
| | voltage supply | Limited Voltage/Current |
| | UL approval number | A025 |
| | File number UL | E174191 |
| Mechanical data | | |
| Weight [g] | 157.5 | |
| Housing | rectangular | |
| Sensing face | 5 positions selectable | |
| Mounting | non-flush mountable | |
| Dimensions [mm] | 40 x 40 x 54 | |
| Material | PA; brass white bronze coated | |
| Displays / operating elements | | |
| Display | target in measuring range | 1 x LED, yellow lights |
| | target outside measuring range | 1 x LED, yellow flashing |
| | Power | LED, green |

IM5141



Inductive analog sensor with IO-Link

IMC4026A1PKG/IO/US

Remarks

Pack quantity


1 pcs.

Electrical connection - plug

Connector: 1 x M12; coding: A



Connection



| | |
|---|---------------|
| 1 | L + |
| 2 | OUT |
| 3 | L - |
| 4 | OUT / IO-Link |